TP9135/40 SPECIFICATIONS



Tough, reliable and interoperable.

TP9135/TP9140 portable radios provide affordable and reliable digital communications for Public Safety users who need exceptional audio clarity without provision for all possible features or configurations.



KEY FEATURES

- Radios can be used on analog, P25 conventional, trunked and simulcast networks
- ▶ Ease of operation: all user controls and menu functions are identical across all the Tait P25 portables, mobiles and hand-held control heads
- ▶ Tested beyond MIL-STD-810C, D, E and F Tait performs tougher drop tests, then performs ingress and other tests on the same radio
- ▶ Supports individual, group, broadcast and emergency calls
- ▶ Programmable power settings and intelligent batteries
- ▶ Emergency features for staff safety include Man Down and Lone Worker
- Advanced voting optimizes channel reception
- Comprehensive scanning features including P25 talk group, priority, dual priority and editable scanning.















Tait Tough Radio

Reliable and durable TP9135/TP9140 portable radios have been built to withstand the accidental knocks and the extremes of nature.

Dual shot molding provides builtin shock absorption, while a unique and patented battery clasp mechanism eliminates threat of the battery dislodging when the radio is dropped.

Interoperability assured

Genuine open standards ensure choice, value and responsiveness during routine operations or crises.

Digital audio clarity

Crystal clear digital audio allows precise communication even in noisy situations.

Analog operation for phased transition to P25 digital

Protect your current analog investment and migrate to P25 at your own pace.

Analog mode allows communication between various partner agencies signaling options including MDC1200 encode/decode and Two Tone decode.*

*A separately enabled option.

Tailored functionality

This radio will provide the essential network performance required by Public Safety users. For more advanced functionality users should consider investing in the TP9155/60 for long term flexibility.



Above: A TP9140 with yellow front panel shown.

More front panel colored options are available. Please contact your local Tait representative for more information.





GENERAL				
Frequency ranges	Frequency band [†]			
VHF	136-174MHz*			
UHF	380-420MHz* 400-470MHz* 450-530MHz			
700/800MHz	Transmit 762–776MHz 792–825MHz 851–870MHz	Receive 762-776MHz 851-870MHz		
Frequency stability	±1.5ppm (22°F to 140°F/-30°C to 60°C)			
Channels/zones	1,000 channels/30 zones			
Talk groups	26 talk group lists comprised of up to 50 members each			
Scan groups	300 with up to 50 members each, maximum of 2,000 members total			
Dimensions (DxWxH)	1.9 x 2.6 x 6.6in (47 x 67 x 167mm)			
Weight (includes NiMH battery) (includes Li-Ion battery)	20.4oz (580g) 16.4oz (480g)			
Interfaces	Four-line full dot matrix LCD			
Channel spacing	12.5/15/20/25/30kHz			
Frequency increment	2.5/5/6.25			
Operational temperature	-22°F to 140°F (-30°C to 60°C)			
Sealing	IP54 dust and rain			
Rated audio	>500mW			
Analog signaling options	MDC1200 encode/decode, Two Tone decode, PL (CTCSS), DPL (DCS)			

TRANSMITTER					
	VHF	UHF	700/800MHz		
Output power	5W, 3W, 2W, 1W	4W, 2.5W, 2W, 1W	3W, 2.5W, 2W, 1W		
Modulation limiting 25/30kHz channel 20kHz channel 12.5kHz channel	±5kHz ±4kHz ±2.5kHz				
FM hum and noise (typical) 25/30kHz channel 12.5/15kHz channel	-48dB -42dB	-41dB -37dB	-40dB -34dB		
Conducted emissions (typical)	-75dBc	-75dBc	-70dBc		
Audio response (analog) 12.5/15kHz 25/30kHz	300-2550Hz +1/-3dB 300-3000Hz +1/-3dB				
Audio distortion (analog)	<5% @ 1kHz, 60% modulation				
ransmit attack time (TIA/EIA 102)	50mS				
Duty cycle	1min Tx, 4min Rx for 8hrs @ 140°F (60°C)				

© Tait Limited 2013. www.taitradio.com



RECEIVER (TYPICAL FIGURES SHOWN)					
	VHF/UHF	700/800MHz			
Analog sensitivity 12dB SINAD	0.28µV (-118dBm)	0.28µV (-118dBm)			
Digital sensitivity (TIA/EIA-102) 5%BER	0.22µV (-120dBm)	0.22µV (-120dBm)			
Intermodulation rejection (TIA/EIA 102)	-78dB	-78dB			
Adjacent channel selectivity 25/30kHz channel (TIA/EIA 603) 12.5kHz channel (TIA/EIA 102)	-73dB -63dB	-70dB -60dB			
Spurious response rejection	-75dB	-70dB			
Residual audio noise ratio (TIA/EIA 102)	45dB	45dB			
Audio distortion @ rated audio	<3%	<3%			

BAIL ITA	DV CTAI	NDARDS 8	100 D E	ANDE
W 1 - 1 - 4				

A 11 11 MIL OFF	and all all	n 1
Applicable MIL-STD	Method	Procedure
Low pressure	500.4	2
High temperature	501.4	1, 2
Low temperature	502.4	1, 2
Temperature shock	503.4	1
Solar radiation	505.4	1
Rain	506.4	1, 3
Humidity	507.4	1
Salt fog	509.4	1
Dust	510.4	1
Vibration	514.5	1
Shock	516.5	1, 4

BATTERY

NiMH 2400mAh Intelligent battery options Li-Ion 2400mAh

Battery shift life (NiMH/Li-Ion) >12 hours 5/5/90

CHARGER

Charger options (NiMH, Li-Ion) Fast desktop smart charger 6-way multi charger Vehicle charger

EGU	II A'	$T \cap I$	DV	DA.	TA
 441	J -7 ∴1				1 🕰

USA	VHF UHF 800MHz	CFR 47 Parts 22, 7	CFR 47 Parts 22, 74, 90, 90.210 CFR 47 Parts 22, 74, 90, 95A, 90.210 CFR 47 Parts 22, 90			
Canada		RSS-119	RSS-119			
Europe		EN300 086, EN30	EN300 086, EN300 113, EN301 489, EN60950-01			
Australia/Ne	ew Zealand	A3/NZS4295				
Type approval		FCC	Industrie Canada	NTIA		
VHF UHF		CASTPAB1A	737A-TPAB1A	136-174MHz* 380-420MHz*		
	800MHz	CASTPAH5A CASTPAH6A CASTPAK5A	737A-TPAH5A 737A-TPAH6A 737A-TPAK5A	400-470MHz*		
Emission de	signators	10K0F1D, 10K0F1E, 10K0F7D, 10K0F7E, 11K0F3E, 12K7F1D, 16K0F3E, 6K60FZD, 7K70F1D, 8K10F1D, 8K10F1E, 8K10F7D, 8K10F7E, 9K60F2D				
ESD standar	rd	IEC 61000-4-2				

Specifications are subject to change without notice and shall not form part of any contract. They are issued for guidance purposes only.

*Tait confirms that this product model conforms with NTIA requirements.

The word "Tait" and the Tait logo are trademarks of Tait Limited. Tait is an ISO 9001: 2008 and ISO 14001: 2004 certified supplier.

Authorized Partners

Please note that this product does not offer encryption capability and there is no upgrade path for this. If encryption may be required Tait recommends the TP9155/ TP9160 portable radios.



^{*}Please note that not all frequency bands and power outputs are available in all markets. For further information please check with your nearest Tait office or authorized dealer.